

CITY THEATRICAL

NEW YORK • LONDON

475 Barell Ave., Carlstadt, NJ 07072
Voice: 800-230-9497, 201-549-1160
Fax: 201-549-1161

SHoW DMX SHoW Baby™ Wireless DMX Transceiver

The SHoW DMX SHoW Baby™ represents a breakthrough in plug-and-play wireless DMX and RDM transmission, and can be used either as a wireless DMX transmitter or receiver. All you need now to set up a SHoW DMX wireless DMX system is two SHoW DMX SHoW Baby units and two minutes!

The SHoW DMX SHoW Baby features include:

- SHoW DMX Neo™ 2.4GHz Frequency Hopping Spread Spectrum (FHSS) Radio
- Wirelessly broadcast and receive a full Universe (512 slots) of DMX
- Robust wireless DMX512 and RDM data transmission
- Extremely low 7mS latency
- RDM proxy and responder functions
- Instant plug-and-play configuration: *For a Transmitter, connect DMX IN, for a Receiver, don't!*
- 72mW ETSI broadcast power
- Mounting Bracket for installation with C-Clamps or similar hanging hardware
- Included CL2 12VDC Power Supply with international plug set
- Included 2dBi Omni-directional Antenna
- Neutrik® 5P XLR Connectors for DMX IN and DMX OUT



Mechanical

- NEMA 1 Steel and ABS enclosure
- Aluminum Mounting Bracket for ½" Hardware for C-Clamp or other hanging hardware

Electronic/ Functional Features

- DMX IN and out via Neutrik 5P XLRs
- LED indicators:
 - Tx (set as transmitter)
 - Rx (set as receiver)
 - Data (data present)
 - RF Signal Strength (4 LEDs) Low to High



Compliance:

- RoHS Compliant
- CE Certified
- FCC Certified

CTI Part #: 5702

Power: 12V 200mA DC Power Input (100-240VAC 50/60 Hz to 12VDC Adapter provided)

Weight: 0.4 lbs

Dimensions: 3.625"W x 1.8"H x 3"D