

CITY

THEATRICAL

NEW YORK • LONDON

Installing a firmware update in the CTI 5906 or 5907 Multiverse® Receiver Card

To install a firmware update:

Download the new firmware .zip file from the CTI Website. It can be found in the download section of the product page.

You will need a PC or Mac to plug into the dimmer's USB micro B connector. When in boot load mode, the dimmer's USB port will act as a flash drive for you to copy the files to.

1. Enter boot load mode on the receiver card by applying power while holding down the ID button. Keep it pressed until the Signal Quality LEDs chase with a 1 second step rate. It is easiest to use the USB connector to power the dimmer.
2. Delete any files that already exist on the dimmer's flash drive when it shows up on your computer
3. Un-zip the downloaded file and transfer all firmware files to the root directory of the dimmer's drive.
4. Press the ID button after all files have been copied to begin the update process
5. Wait for all firmware files to be programmed as indicated below:
 - a. Signal Quality Low: Solid green followed by rapid flashing (Host CPU)
 - b. Signal Quality Mid: Slow flash followed by rapid flashing (Radio CPU)
6. Once complete, if successful, the receiver card will re-boot into normal mode, otherwise the errors will be indicated as below.

Errors:

Status Red, Signal Quality Low Flashing = Host update failure

Status Red, Signal Quality Mid Flashing = Radio update failure

US HEADQUARTERS
475 BARELL AVENUE
CARLSTADT, NEW JERSEY 07072
TEL 800 230 9497 / 201 549 1160
FAX 201 549 1161

www.citytheatrical.com

LONDON OFFICE
UNIT 1-3 WYVERN ESTATE, BEVERLEY WAY
NEW MALDEN, SURREY KT3 4PH
TEL +44 (0) 20 8949 5051
FAX +44 (0) 20 7183 6061