



With tens of thousands of units sold since their introduction in 2011, SHoW Baby plug and play transceivers set the standard for ease of use and reliability at an affordable price point. The addition of Multiverse radio technology enhances the performance even more.

Multiverse® SHoW Baby® is a wireless DMX transceiver that delivers breakthrough plug and play wireless DMX and RDM transmission **right out of the box**. In its default mode, it works exactly like SHoW Baby 6 with six user selectable SHoW IDs.

By connecting an RDM controller, like DMXcat® Multi Function Test Tool, all of the revolutionary new 2.4GHz Multiverse SHoW IDs are accessible. Users can add to their existing SHoW Baby systems, build new single universe Multiverse systems, or use **Multiverse SHoW Baby** as a receiver on multiple universe systems with a Multiverse Transmitter*.



What's in the box



SPECIFICATIONS:

| P/N | Frequency | Universes |
|------|-----------|-----------|
| 5900 | 2.4GHz | 1 |

| Physical | | |
|-----------------|--|------------|
| Length | 92mm | (3.625 in) |
| Width | 76mm | (3.0 in) |
| Height | 46mm | (1.8 in) |
| Antenna | 2dBi | |
| User Interface | One button/indicator lights | |
| Construction | Injection molded plastic, black | |
| Power Connector | 5.5mm x 2.1mm, center positive, 9mm mating depth** | |
| Data Connector | Neutrik® 5P XLR Connectors for DMX IN and DMX OUT | |

| Electrical | |
|--------------------|-------------------------------------|
| Power | 7.5-30VDC, 1W |
| Broadcast Power | 2.5mW, 8mW, 25mW, 80mW |
| Broadcast Modes | Adaptive, Full, Low, Mid, High, Max |
| DMX Burst Modes | Auto Dynamic |
| Ethernet Protocols | N/A |
| SHoW IDs | Multiverse: 147; Neo: 70 |
| RF Sensitivity | -95dBm |
| RDM Features | RDM Proxy, RDM Responder |

| Product Information | |
|---------------------|-------------------------|
| Use Environment | Indoor |
| IP Rating | IP50 |
| Compliance | FCC, IC, CE, ARIB, RoHS |
| Warranty | One year |

*Note: Multiverse SHoW Baby (P/N 5900) is compatible with Multiverse Transmitter (P/Ns 5910 and 5911) when used with a Multiverse SHoW ID on the 2.4GHz band.

**Note: This power supply connector is not compatible with Multiverse Node.